

0

**ES RECEIVER SPECS** 









	STR-AZ7000ES	STR-AZ5000ES	STR-AZ3000ES	STR-AZ1000ES
POWER RATINGS <sup>1</sup>	150W + 150W	130W + 130W	120W + 120W	100W + 100W
AMPLIFIER CHANNELS	13.2	11.2	9.2	7.2
PRE-OUTS	13.2	11.2	0.2	0.2
HDMI INPUTS <sup>2</sup>	7 in/2 out	7 in/2 out	6 in/2 out	6 in/2 out
8K & 4K/120HZ HDMI INPUT <sup>3, 4</sup>	4 in/2 out	4 in/2 out	4 in/2 out	2 in/2 out
HDMI 2.1, ALLM, VRR <sup>3</sup>	Yes	Yes	Yes	Yes
360 SPATIAL SOUND MAPPING⁵	Yes	Yes	Yes	Yes
ROOM CALIBRATION	Digital Cinema Calibration IX			
3D SURROUND	Dolby Atmos <sup>®</sup> , DTS: X <sup>®</sup> , 360 Reality Audio	Dolby Atmos <sup>®</sup> , DTS: X <sup>®</sup> , 360 Reality Audio	Dolby Atmos <sup>®</sup> , DTS: X <sup>®</sup> , 360 Reality Audio	Dolby Atmos <sup>®</sup> , DTS: X <sup>®</sup> , 360 Reality Audio
ACOUSTIC CENTER SYNC <sup>6</sup>	Yes	Yes	Yes	Yes
DUAL CENTER SPEAKER	Yes	Yes	_	-
HDR FORMATS	Dolby Vision, HDR10, Hyrbid Log Gamma, IMAX Enhanced			
4K/120P/8K PASSTHROUGH <sup>3,4</sup>	Yes	Yes	Yes	Yes
WI-FI, BLUETOOTH®7	Wi-Fi, Bluetooth	Wi-Fi, Bluetooth	Wi-Fi, Bluetooth	Wi-Fi, Bluetooth
MUSIC STREAMING VIA WI-FI®	Chromecast Built-in, Apple AirPlay, Spotify Connect			
WORKS WITH SONOS®9	Yes	Yes	Yes	Yes
HI-RES AUDIO SUPPORT	Yes	Yes	Yes	Yes
ZONES	Zone 2 + Zone 3			

## SONY



## ES RECEIVER SPECS Continued

	STR-AZ7000ES	STR-AZ5000ES	STR-AZ3000ES	STR-AZ1000ES
12V TRIGGER	3	3	1	-
IR REPEATER	1 in/2 out	1 in/2 out	1 in/2 out	-
RS232C	Yes	Yes	Yes	Yes
PING BUTTON	Yes	Yes	Yes	-
USB SETTINGS SAVE	Yes	Yes	Yes	Yes
GRAPHICAL USER INTERFACE	Yes	Yes	Yes	Yes
FRONT PANEL SETUP	Yes	Yes	Yes	_
DETACHABLE POWER CORD	Yes	Yes	Yes	Yes
ES 5-YEAR WARRANTY	Yes	Yes	Yes	Yes
MOBILE APPLICATION <sup>6</sup>	Sony Music Center	Sony Music Center	Sony Music Center	Sony Music Center
DIMENSIONS (WxHxD)	17 in x 7 ¾ in x 17 ¾"	17 in x 7 ¾ in x 17 ¾"	17 in x 7 ¾ in x 17 ¾"	17 in x 6 ¼ in x 13 1/8"
WEIGHT (Approx.)	48 lbs	42.6 lbs	41.15 lbs	20.9 lbs
COMPATIBLE ACCESSORIES	WSRE2 Rack Ears	WSRE2 Rack Ears	WSRE2 Rack Ears	WSRE2 Rack Ears
WIRELESS REAR SPEAKERS & SUBWOOFERS Compatible and (Sold sep.)	SA-RS3S & SA-RS5 SA-SW3 & SA-SW5			
HELPFUL LINKS	Sony Premium Home Link			































<sup>1</sup> STR-AZ7000ES: 150W + 150W (8ohms, 1kHz, 2ch, THD 0.9%) / STR-AZ5000ES: 130W + 130W (8ohms, 1kHz, 2ch, THD 0.9%) / STR-AZ3000ES: 120W + 120W (8ohms, 1kHz, 2ch, THD 0.9%), STR-AZ1000ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ1000ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ1000ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ1000ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ3000ES: 120W + 120W (8ohms, 1kHz, 2ch, THD 0.9%), STR-AZ1000ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ100ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ100ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ100ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ100ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%), STR-AZ100ES: 100W + 100W (8 ohms, 1kHz, 2ch, THD 0.9%

©2023 Sony Electronics, Inc. All rights reserved. Reproduction in whole or in part without written permission is prohibited. Sony and the Sony logo are trademarks and or registered trademarks of Sony Corporation. Bluetooth<sup>®</sup> and the Bluetooth logo are trademarks of Bluetooth SIG, Inc. All other trademarks are trademarks of their respective owners. Features and specifications are subject to change without notice. Screen images simulated.