




CALL BUTTONS

D2100E & D2100EA

D1100E



Illuminated Call Button for DoorBird D21x




Connection options:

- A. One call button connected to the port for one call button (yellow) of the main unit
- B. 2-18 call buttons connected to the Multi-Tenant Module "MTM18A"
- C. 2-56 call buttons connected to the Multi-Tenant Module "MTM56A"



This combination is available through our customized service.

Please contact us via e-mail: [customized@doorbird.com](mailto:customized@doorbird.com)



Illuminated Call Button for DoorBird D11x



Not compatible



Connection option:

- 1-2 call buttons connected to the port for call buttons (CB) of the main unit



Illuminated stainless steel button for DoorBird D1101KH Classic



Illuminated stainless steel button for DoorBird D21x



Connection options:

- A. One call button connected to the port for one call button (yellow) of the main unit
- B. 2-18 call buttons connected to the Multi-Tenant Module "MTM18A"
- C. 2-56 call buttons connected to the Multi-Tenant Module "MTM56A"



This combination is available through our customized service.

Please contact us via e-mail: [customized@doorbird.com](mailto:customized@doorbird.com)



Illuminated stainless steel call button with separate backlit nameplate for DoorBird D21x

SPARE PARTS



Multi-Tenant Module MTM18A

Connection option:

- One Multi-Tenant Module connected to the port for input modules (red) of the main unit



This combination is available through our customized service.

Please contact us via e-mail: [customized@doorbird.com](mailto:customized@doorbird.com)



Multi-Tenant Module MTM14E

**Only one Multi-Tenant module can be connected to the main unit.**



Multi-Tenant Module MTM56A



Module Port Converter MPCOID21 for connecting a second input module on the D21x series



Connection option:

- One Module Port Converter connected to the port for output modules (green) of the main unit



Not compatible



| SPARE PARTS   | D2100E & D2100EA   | D1100E  |
|---|--|---|
|  <p>Fingerprint Reader Module 50</p>                                     | <p>Available combinations:</p> <p>A. One Fingerprint Reader Module connected to the port for input modules (red) for devices with one call button attached to the main unit</p> <p><input checked="" type="checkbox"/> B. One Fingerprint Reader Module connected to the port for output modules (green) with the Module Port Converter "MPCOID21" for devices with Multi-Tenant modules attached to the main unit</p> | <p>Connection option:</p> <p><input checked="" type="checkbox"/> One Fingerprint Reader Module connected to the port for add-on modules (COM) of the main unit</p> <p><b>Not compatible with Multi-Tenant Modules or Keypad-Modules</b></p>   |
|  <p>Keypad Module with 12 stainless steel keys for DoorBird D21x</p>    | <p>Available combinations:</p> <p>A. One Keypad Module connected to the port for input modules (red) for devices with one call button attached to the main unit</p> <p><input checked="" type="checkbox"/> B. One Keypad Module connected to the port for output modules (green) with the Module Port Converter "MPCOID21" for devices with Multi-Tenant modules attached to the main unit</p>                         | <p>Connection option:</p> <p><input checked="" type="checkbox"/> One Keypad Module connected to the port for add-on modules (COM) of the main unit</p> <p><b>Not compatible with Multi-Tenant Modules or Fingerprint Reader Module 50</b></p> |
|  <p>Keypad Module with 16 stainless steel keys for DoorBird D21DKx</p> | <p>Connection option:</p> <p><input checked="" type="checkbox"/> One Keypad Module connected to the port for input modules (red) of the main unit</p> <p><b>Can only be used in combination with a Display Module.</b></p>   | <p><input checked="" type="checkbox"/> Not compatible</p>   |
|  <p>Display Module, Color, 3.5 inch, for DoorBird D21DKx</p>           | <p>Connection option:</p> <p><input checked="" type="checkbox"/> One Display Module connected to the port for output modules (green) of the main unit</p> <p><b>Can only be used in combination with a Keypad Module with 16 keys.</b></p>   | <p><input checked="" type="checkbox"/> Not compatible</p>   |
|  <p>Info Module for DoorBird D21x</p>                                  | <p>Connection option:</p> <p><input checked="" type="checkbox"/> One Info Module connected to the port for output modules (green) of the main unit</p>   | <p><input checked="" type="checkbox"/> Not compatible</p>   |